

ManyGuitar user manual



ManyGuitar user manual

Introducing ManyGuitar	1	FX wizard	8
About this manual	1	Soft clipping final limiter and output stage ..	8
Installing ManyGuitar	2	LFO section.....	8
Installation	2	Other functions	9
Presets	2	Polyphony modes.....	9
Getting to grips with ManyGuitar	3	Pitch bend range.....	9
Understanding the signal flow	3	Microtuning.....	9
Sound source	3	The help buttons.....	9
Selecting a sound.....	3	MIDI CC codes	9
Using the Sound Wizard	4	ManyGuitar soundsets	11
Volume envelope.....	4	MT bass guitars - electric	11
Filter	5	MT bass guitars - synth	12
Amp emulator	5	MT guitars - acoustic	12
The amp section.....	5	MT guitars - electric.....	13
The EQ section.....	6	MT guitars - synth	14
The cabinet emulator	6	Creating your own soundsets	14
Spicing up the sound.....	6	ManyThanks.....	15
Phaser/chorus.....	6	Disclaimer	16
Tremolo.....	7		
Echo.....	7		

Introducing ManyGuitar

ManyGuitar is a guitar and bass sample based synthesizer with over 1 gig of 24 bit samples.

The ManyGuitar sound library includes a wide range of guitars and basses. Each instrument has been extensively multi sampled, often at several velocities and with a mute layer included. In addition to the single note samples, there are some chord sets and also some great lead guitar styles.

This extensive sound library has then been coupled with a highly efficient sample playback engine with a custom amplifier and speaker cabinet emulator and an FX rack designed exclusively for ManyGuitar. This engine allows you to take the Manytone guitar and bass samples to new levels of reality. The amp section also includes a deep amp mode that is suited to bass and other low toned guitars.

The detailed guitar library coupled with the high quality but CPU friendly engine which has been specifically designed for processing guitar samples makes ManyGuitar a very unique instrument.

ManyGuitar will also load soundsets in both Wusik wusikSND and Dash Signature dashSND format (the sample playback engine is based on the Eve One engine from Dash Signature). As well as the libraries that are already available for WusikStation from Wusik and EVE from Dash Signature, all of the existing ManyStation soundsets (including all the add-ons for ManyStation such as Ultimate Bass Kit) can be loaded into ManyGuitar to take advantage of the amplifier/cabinet treatments and the FX rack. Of course, the ManyGuitar soundsets can also be loaded into ManyStation.

About this manual

This manual is intended to help you get the most out of ManyGuitar. However, you don't need to read it to start making music with ManyStation – just call up some presets and you're good to go.

Please take the time to familiarize yourself with the manual – it gives a lot of detail about the sounds and tells you how to use some of the features which may not be immediately obvious. Please ensure you that you have read this manual before you call for help.

If you have any problems with ManyGuitar, then go to <http://forum.manytone.com> or you can click on the “forum” button in the Manytone website <http://www.manytone.com>. However, we do recommend you read this manual before you call for help.

Alternatively, drop an email to support@manytone.com – you will generally find that you get a swifter response by using the forum.

This manual was written by me, Simon Cann. If you don't like it, blame me, not Manytone. If you find any errors, please let me know (email to: manytone@noisesculpture.com). If any explanation is not clear, please let me know (same email address) and I will clarify the wording. If you write, please let me know whether it is the concept that is difficult or the wording (or both). If you do email, please quote the text that troubles you.

Installing ManyGuitar

Installation

ManyGuitar comes as several compressed files which need to be uncompressed. The decompression is controlled by an installer program. For existing ManyStation/WusikStation users, the installer will add the soundsets to an existing Manytone/Wusik directory. For new users, the installer will create a new directory. The first time that you run ManyGuitar, a window will ask you for the library folder. At this stage, simply select the folder in which you installed the sample library.

For fuller details about installation process, check the readme.txt file.

Presets

ManyGuitar comes with a range of presets which load automatically with the default bank.

Other banks and presets will be made available in due course. You can load these banks and presets through your host. If you don't know how to save and load preset or banks, please refer to your host's documentation.

Getting to grips with ManyGuitar

Understanding the signal flow

Once you understand the signal flow in ManyGuitar, you will understand better how to control the sound and get the tone you want (you will also understand how this manual is set out!!)

ManyGuitar is set up to run in a very similar manner to how an electric guitar is set up with an amp and FX:

- the sound originates from the sound source – you select the soundset you want (for instance one of the Fender Strat samples)
- the sound then passes into the volume envelope – this controls the amplitude of the sound over time (for instance how quickly the note’s attack is heard – as an example, you could use the volume envelope to change a picked note to sound like a “bowed” note)
- at the envelope stage, you can also change the tuning of the patch and set the volume of the sound source (much like you would turn the volume knob when playing a real guitar)
- the note then passes into the filter which allows you to change the tone of the sample, and of course, the filter has its own envelope
- next the sound passes into the amplifier emulator – this give you four main controls:
 - o the amp model (high gain, tube and deep)
 - o the drive amount – this in turn is affected by the output level of the sound source set by the level knob in the volume envelope
 - o the four band EQ section (bass, mid, high and presence), and
 - o the speaker cabinet emulator
- after the amp, the signal passes to the phaser/chorus FX, then to the tremolo section, and next to the echo unit, and
- finally the signal passes to the limiter and then out of the plug.

Sound source



Selecting a sound

In the top left-hand corner you select the sound source:

- the middle line selects the category, and
- the bottom line selects the individual soundsets within the category.

You can select the category and the soundset, either:

- by clicking on the down arrow on the right-hand side and selecting the category/soundset from the drop-down menu, or

- you can browse up and down by clicking the appropriate arrow on the left.

Using the Sound Wizard

In the top line of the sound source selector, you can click on the “Sound Wizard”. Once you have selected a sound source, the sound wizard will let you select one of a number of preset settings from a drop-down menu.


These settings will change all the parameters of the instrument, with the exception of the sound selected. This will allow you to quickly try out different envelope and filter settings.

Volume envelope

The volume envelope allows you to change the volume of the sound source – this means that the sound of the guitar samples can be radically changed. Typically the attack of a guitar’s note is very fast – the volume envelope allows you to change this so, for instance, you can emulate a player “bowing” a guitar’s note or create completely unnatural sounds.

The envelope has four controls to shape the sound:

- A: attack time – the time it takes the sound to reach its maximum level
- D: decay time – the time it takes the sound to reach the sustain level after it has reached the maximum level
- S: sustain level – the level at which the sound sustains, after the attack and decay phases, while a note is held, and
- R: release time – the time it takes for a note to decay from the sustain level to zero after a key is released.



If you want to retain a sample’s natural envelope, you should set the attack and decay times to the minimum, the sustain level to the maximum and then adjust the release time to taste.

In addition to the envelope, there are several other controls in the envelope section:

- The velocity sensitivity (marked “vel sense”) knob gives you control over the dynamic response of ManyGuitar. Turning the control to the right will make ManyGuitar more sensitive to incoming MIDI velocity and moving it to the left will make it less sensitive. Moving the velocity sensitivity knob to the extreme left will remove any dynamics from MIDI messages, therefore every note will be played at a fixed velocity regardless of the MIDI velocity received.
- The knob marked with a triangle (amp scaling) lets you scale the sound level across the keyboard (starting from C1, up to C5). Using this control you can make the volume decrease smoothly over either the low or the high range of the MIDI keyboard. This is often called “volume



key-tracking". In the default (vertical) position, this control has no effect.

- The knob with an ADSR envelope graphic controls the time scaling of the volume envelope. This allows an increase or decrease in the speed of the attack, decay and release stages of the volume envelope over the MIDI keyboard. This is useful when emulating real instruments: many of them, for example the guitar, have a decreased sustain time at higher pitches. This is also called "envelope speed key tracking".
- The level knob controls the level of the output and comes before the amp and the effects section. This knob acts like the volume knob on a guitar and has a direct effect on the amount of distortion introduced by the amp emulator and the tone of that distortion.
- The coarse and fine knobs allow for adjustment of the instrument's pitch. The coarse control can shift the sound by +/-12 semitones and the fine control allows adjustments of +/- 50 cents (or a semitone).
- The red R reset button resets the level and the tuning controls to their default values.

Filter

ManyGuitar has a multimode filter giving three filter options:

lp: low pass – frequencies above the cut-off frequency will be cut

hp: high pass – frequencies below the cut-off frequency will be cut, and

bp: band pass – frequencies above and below the cut-off frequency will be cut leaving only frequencies around the cut-off frequency to be heard.



These filters have a 12dB/octave slope and, unlike conventional state variable filters, follow a design that allows a "fat sounding" resonance and a high accuracy in term of frequency response, keeping the CPU usage very low at the same time.

The cut-off frequency of the filter can be set using the "cut" knob and the filter's resonance is controlled by the "resonance" knob.

You can also use the filter envelope to control the cut-off frequency – the "env" knob sets the extent to which the envelope controls the filter cut-off frequency. The control can be either positive (opening up the effect of the filter) or negative (closing down the filter).

As with the volume envelope, the "vel sens" knob governs the extent to which a note's velocity controls the cut-off frequency.

Like the volume envelope, there are the two tracking knobs. The key tracking knob lets the filter follow the pitch of the notes when set to the maximum value (to the right). In this case, the cut-off frequency increases as the pitch increases. If set to the middle the filter cut-off will remain constant across the whole keyboard. If set to the left the cut-off frequency will increase as the pitch decreases. The time scale knob increases or decreases the speed of the attack, decay and release stages across the MIDI keyboard.

The filter can be bypassed (turned off) by using the power switch.

You can directly control the filter cut-off frequency with either the modulation wheel or aftertouch. The two small knobs to the right of the power switch (labeled "m" for modulation wheel and "a" for aftertouch) set the amount of change. The cut-off change can be either positive or negative.

Amp emulator

There are three sections in the amp emulator. Each can be used independently (and switched in and out independently). However, you will find you achieve better results by using the three sections together.

The amp section

The amp section is turned on by flicking the switch to the left of the drive knob and the amp selector.

The amp has three settings:

- high gain: when you *REALLY* need to rock
- tube: when you're looking for a more subtle and vintage approach, and
- deep: ideal for when you're using lower toned instruments (such as a bass).

Once you have chosen the amp, then adjust the drive control to taste. You may find you get a more natural overdrive sound by turning **DOWN** the drive knob and turning **UP** the level knob in the volume envelope section.

The EQ section

The EQ section is turned on by flicking the switch to the left of the bass knob.

The EQ section has four bands – bass, middle, treble and presence (which controls the frequencies above the treble control). Each knob can cut and boost the corresponding band.

The cabinet emulator

The speaker cabinet emulator gives eight speaker options (in addition to bypass):

- closed 4 x 12"
- open 2 x 12"
- closed 12"
- closed 10"
- closed 8"
- closed 4"
- closed 2", and
- closed 15" (bass)

Click on the drop down menu to choose the right option for your patch.

Unless you are after a particularly harsh effect, you will usually always want to use the speaker emulator when you have an overdriven sound.

Spicing up the sound

The FX rack gives you six FX units:

- mono phaser
- stereo phaser
- stereo chorus
- quad chorus
- tremolo
- echo (three varieties - warm, crush and light)

Each effect can be switched in or out with the on/off switch next to the effect.

Phaser/chorus

You can select one unit at a time in the phaser/chorus section.

Phaser

The mono phaser in ManyGuitar features a clean four stage phaser, based on classic analog phaser design.



The controls for the phaser are noted *above* the phaser/chorus control knobs. The controls available are:

- rate which controls the sweep frequency of the phaser's filters
- depth which controls the amount of frequency excursion of the filter
- shift selects the centre frequency of the sweep, and
- feedback which controls the amount of resonance of the phaser.

The stereo phaser, splits the phaser into two phasers, one acting independently on each stereo channel. This gives more vitality to the sound. To ensure the monophonic compatibility you should always check the sound produced by the phaser in stereo mode in mono.

Chorus

ManyGuitar has two chorus units: a double chorus and a quad chorus. Essentially, these act as two or four chorus units giving a progressively richer (and therefore fatter/more dominating) sound.

The chorus unit works by adding a delayed, modulated signal to the dry signal. This gives the effect of there being several sounds rather than just one.

The controls for the chorus are noted *below* the phaser/chorus control knobs. The controls available are:

- rate which controls the frequency of the oscillator which modulates the delayed signal – at faster rate settings (knob turned to the right) the effect may sound like vibrato
- depth which controls the maximum amount by which the pitch of the delayed, modulated signal may be changed
- chorus mix which controls the wet/dry mix, and
- spread which controls how widely the effect is spread over the stereo spectrum.

Tremolo

This is a conventional tremolo effect based on vintage design with rate and depth parameters.



Echo

The ManyGuitar echo unit has been designed to give you a wide range of musical sounds.

The echo can be configured in three modes:

- warm: this echo repeats the original sound as-is, except a soft high cut filter is applied to give a warmer sound
- crush: this echo behaves more like an old tape-based echo unit, so it has a poor high-frequency response, a limited amount of distortion and the pitch also fluctuates slightly, and
- light: this echo is suitable for more modern musical styles. It has a narrow frequency band and a higher distortion. The pitch fluctuates significantly.



The delay time of the echo can be set using the time knob. The delay times range from 4 to 2000 milliseconds. Alternatively the delay can be synchronized with the host tempo by selecting a rhythmic division unit from the menu which pops up when you click on the sync display.

When synchronized, the time knob lets you choose how many times the basic rhythm division the echo should last.

The feedback knob controls the amount of the echo output that will be fed back to the echo input. Higher values will result in more echoes.

The stereo knob lets you set an additional delay between the left and the right stereo channel. When this parameter is not set to zero It is important to check the sound output in mono (left channel mixed with the right) to ensure mono compatibility of the mix.

The mix control lets you balance the amount of the original signal and the echo.

FX wizard

The FX wizard is there to help you get your FX added quickly. It adds a range of preset FX: all you have to do is select one from the drop down menu.



Soft clipping final limiter and output stage

The output level is controlled by the volume slider.

To the right of this is the output level meter – this may be switched off (by the switch to the meter's right) in order to conserve CPU usage).

Beneath the volume slider and output meter is the soft clipping control. This is engaged by clicking on the red LED (which is lit when the limiter is active). This limiter controls the output and may be useful to avoid harsh digital distortion when the audio signal is boosted by extreme filter or FX.



LFO section

ManyGuitar has one low frequency oscillator (LFO) for each voice but with several routing options.



On the left of the LFO section you will find the power switch to turn the LFO on or off.

Next to the switch you see a small numerical display. This display can show either the frequency (in hertz) of the LFO (when sync is off) or the multiplier of the tempo division when the LFO is synchronized to the song tempo. This value (whether hertz or multiplier) is set using the rate knob.

Below the LFO frequency display is a drop-down menu to select the rhythmic division. You can also select "off" to set the value of the LFO when it is not synchronized to the song's tempo.

Each note has its own independent LFO, and the LFO starts immediately when the note starts. You may want to introduce a delay before the LFO starts, and you can do so using the delay control group:

- the "delay" knob controls the time before which the LFO has effect (this delay can also be synchronized), and
- the attack knob which controls the time over which the effect of the LFO fades in.

If both the delay and the attack knob are set to zero, the LFO will have immediate effect.

The LFO can control the pitch, the cut-off frequency of the filter and the amplitude of the sound. To set the LFO to control either or all of these three elements, use the knobs marked pitch, cut and amp. The middle value (12 o'clock) corresponds to zero depth (ie no modulation) for the pitch and cut knobs. Turning these two knobs to the left allows for inverted modulation of the pitch and filter cut-off frequency.

The three parameters can also be controlled by the modulation wheel and aftertouch. The amount of modulation by can be controlled by the small knobs marked "m" (for modulation wheel) and "a" (for aftertouch) to the left of each of the main knobs.

Other functions

Polyphony modes

ManyGuitar has several playing modes to help you get a more natural performance:

- polyphony – when this mode is selected, the maximum number of voices (between 4 and 100) is selected in the left hand box above the polyphony button
- mono – when this mode is selected only one voice will play, irrespective of how many voices have been selected
- legato – when this mode is selected, if you hold a note and play a new note, the pitch will slide from the old to the new note. The slide time is controlled by the glide knob. There is the further option to set the glide time to either:
 - o constant speed (so the rate of glide is constant, in other words an octave glide will take twelve times as long as a semitone glide), or
 - o constant time (so the glide time from one note to another takes the same time irrespective of the interval between the notes, so a semitone glide will take as long as an octave glide).

This glide effect is great for fretless bass type slides.



Pitch bend range

On the right of the Voices value you will see the pitch bend range drop-down menu, which allows you to select the maximum bend range between 0 and 12 semitones.

Microtuning


ManyGuitar supports microtuning by allowing TUN files to be loaded.

For more info on TUN files and microtuning please visit:

<http://www.xs4all.nl/~huygensf/scala/>

http://www.xs4all.nl/~huygensf/scala/Scala_TUN_Tutorial.pdf

<http://www.microtonal-synthesis.com/>



The help buttons

On the top right of the ManyGuitar interface you will see three round buttons:

- clicking the “?” button will display the on-line help
- Clicking the “i” button will display the “about” box with information about copyright, the credits and the software version, and
- clicking the “s” (for skin) button will display the skin selector menu. From this menu you can choose one of the installed skins available for ManyGuitar (such as the Miniguitar skin – see graphic below). To display a new skin selected simply close the plug-in window and reopen it.



MIDI CC codes

You can use midi CC codes to control ManyGuitar. For a list of CC codes, click on the “?” in the top right hand corner of ManyGuitar.



ManyGuitar soundsets

In designing ManyGuitar the focus has been on creating detailed and highly playable sounds. Some of the soundsets include over 70 multi-samples for stunning levels of detail, with special layers (such as slides, string noise and guitar palm mutes) in addition. All samples were taken at 24 bit.

Manytone went to extremes in developing the ManyGuitar soundsets: every wave was edited by hand. If you open up any of the waves in a wave editor you will see that the start of the sample begins at zero and all samples fade to zero. This attention to detail ensures that you have the highest quality source material and will not hear any clicks or other unwanted audio artefacts.

All of the soundsets have been recorded in their natural state so it is up to you to add any processing. Manytone could have added some processing at the sampling stage but that would have restricted the flexibility of the soundsets. However, you will hear that many of the patches take advantage of ManyGuitar's amp and FX which you can, of course, edit.

The notes below tell you a bit about the soundsets and how the samples are intended to be used. The patches also give many examples of how you can use these soundsets. However, as always, don't let our suggestions stifle your creativity!

ManyGuitar comes with over 1.2 gig of soundsets. This includes:

- the original 638 meg of guitars and basses that are included with ManyStation, PLUS
- 645 meg of newly sampled guitar and bass soundsets exclusive to ManyGuitar.

The new soundsets have been marked with an asterisk (ie "*") in the list below.

MT bass guitars - electric

		This soundset is taken from the same 2002 Fender Jazz bass guitar as the FJazz bass sets (see below) but is a completely different set of samples from the same recording session. It sounds similar to the Jazz Bass but this set is special in that it is mapped with a slightly muted palm note on the upper
* BassCompSplit	46 multi-samples	octaves and a regular full note on the lower octaves. This allows for some very fast and realistic true staccato style playing where you can vary the same note back and forth by playing the different octaves of the same note. This leads to more realistic bass tracks as you can avoid the machine gun sound on faster parts.
BassElecFngLng	33 multi-samples	This soundset was sampled from a beautiful 25 year old Vantage bass guitar that has a brass nut and bridge. This guitar really plays and feels great. The samples were recorded with the strings played with the finger. All major notes were sampled with string noise and slides mapped on the keyboard below the low E.
BassElecMute	32 multi-samples	All major notes were sampled with string noise and slides mapped on the keyboard below the low E.
BassElecSlap	32 multi-samples	This soundset is a punchy slap bass. All major notes were sampled with string noise and slides mapped on the keyboard below the low E.

* BassFingerFine	34 multi-samples	This bass tone is achieved by playing with free strokes rather than the more common rest strokes used in bass playing. This technique gives the notes a sharper, finer tonal quality. The cleaner tone is suitable for Jaco-esque bass lines.
* BassFingerWarm	29 multi-samples	In this soundsset the strings are plucked directly over the pickups giving a warm timbre. This is the most common plucking position in bass playing and is very versatile for different styles of music.
FJazzBass Mute	29 multi-samples	This palm muted bass guitar was sampled from a 2002 Fender Jazz bass.
FJazzBass Set1	29 multi-samples	A great bass sound with nice long samples. Sampled from a 2002 Fender Jazz bass. These JazzBass sets will give your tracks that real punchy bass guitar sound.
FJazzBass Set2	29 multi-samples	This is the same guitar as the above FJazzBass set, but this is a different set of samples made with a different pickup setting on the guitar. Also recorded with string noise and slides mapped in the soundsset for added realism.
FJazzBass Set3	11 multi-samples	The same Fender bass guitar with a slightly different sound. Also with string and slide noise mapped in.
StringNoiseEbass1	10 multi-samples	This is a separate string noise set that you can use with other basses you may have which do not have string noise and slides.
StringNoiseEBass2	7 multi-samples	String noise and slides from the Fender Bass.

MT bass guitars - synth

BassHeavyGtrSyn	20 multi-samples	A nice heavy and hard style bass.
BassRockGtrSyn	8 multi-samples	Same as the above set but different samples with a different sound.

MT guitars - acoustic

* Gtr12StringMic	72 multi-samples	A fresh set of strings on this 12 string lends to the fantastic sound. Recorded through a Rode mic and played with a medium pick. This set has 2 layers with a mute layer mapped on the lower velocities and a sustained picked layer on top. This set also features sampled dropped D and dropped C tuning on the low E string.
* Gtr12StringMicMute	41 multi-samples	This is the mute layer from the above set mapped to its own set for when you need a full on mute sound.
* Gtr12StringPU	33 multi-samples	An old Yamaha 12 string acoustic guitar recorded with a Dean Markley pickup fitted in the sound hole. This set sounds a lot like an electric 12 string.
GtrAcousticSuziMic	40 multi-samples	A beautiful acoustic guitar sampled with a Rode microphone.
GtrAcousticSuziPiezo	38 multi-samples	The same guitar as above with a piezo pickup instead of a microphone.

* GtrNylonFinger	59 multi-samples	This nylon guitar soundset has two layers. At regular velocities, the guitar plays normally. At the top end of the velocity range when you hit the keys harder you get a nice slide into the note.
GtrSixString	22 multi-samples	Another nice acoustic steel string guitar. This guitar was hand made in Canada.
GtrSixStringAmped	22 multi-samples	Same guitar as above but with some amp simulation for that live "unplugged" type sound.
GtrStringNoiseAc	10 multi-samples	Some acoustic noise and slides to add some realism to your guitar tracks.

MT guitars - electric

GtrFStratCleanNF	61 multi-samples	This is a very nice clean sampled 1996 Fender USA Stratocaster. This is the neck pickup, finger picked. Every note on the guitar was sampled and meticulously edited to work in ManyGuitar. It also has the string and slide noise from the same session mapped on the keyboard to the left of the low E. This set is sampled clean so that you can apply your own FX and amp simulations etc.
GtrFStratCleanNP	61 multi-samples	A completely different set of samples from the same 1996 guitar. This time we recorded them using a pick. Every note on the guitar was sampled.
GtrFStratCleanNPMute	38 multi-samples	This soundset plays great and comes from the same recording sessions as the other Strat sets.
GtrFStratDistAmpBP	34 multi-samples	This is one fantastic heavy lead guitar soundset. It is the same guitar as the clean Strat but with a biting amp and distortion blended sound.
GtrFStratPwrChrdBP	20 multi-samples	Great for when you need some smooth power chords in your track. This set also captures the amp and distortion sound.
* GtrFunk	45 multi-samples	This soundset captures a buzzing, muted style of guitar playing. It is suitable for rhythm guitar as well as lead parts. This soundset is very dynamic, featuring two velocity layers. The quiet velocity layer has a tighter muted sound, while the loud velocity layer, although still partly muted, has a longer sustain.
* GtrLeadGuitar1	79 multi-samples	The guitar in this soundset was sampled at the 12th position, which is very common in lead guitar playing. This soundset includes three velocity layers, a normal sustained tone, a bluesy bend, and a hammer-on.
* GtrLeadGuitar2	38 multi-samples	This is a jazzier lead guitar soundset. It has a deep tone suitable for jazz due to the heavy strings used on the guitar. The strings were picked closer to the neck of the guitar, contributing to the depth of the tone. This soundset has two velocity layers, a quiet palm-muted layer, and a normal sustained layer.
GtrStringNoiseElec	14 multi-samples	Once again the string and slide noise from the clean Strats in their own soundset so you can use them for effect, or with other guitar sets that may not have this added realism.

GtrTele567Chords is one really cool chord set. It uses three octaves to spread the major blues/rock style power chords in playable octaves.

The root chord is mapped on the lower octave and the 6th and 7th chords on the following octaves. This allows you to play each note of each octave to sound a chord progression that works for a lot of musical styles.

* GtrTele567Chords	37 multi-samples	Further, on the upper octave you will find the individual notes. These notes are the notes that a guitarist would throw in between chords when playing the above chord progressions. For example a typical note in the E chord progression that a guitarist would throw in with chords in Blues is a G#. In an A Chord progression the guitarist might use a C#. Those notes and all other important notes for this style are sampled and mapped on the top octave. Another cool feature of this is that you can also add these notes to the original chords to make new chords and sounds.
* GtrTeleHarmonics	12 multi-samples	This set has 2 velocities of harmonics from each of the Telecaster's 6 strings. Mapped over the keyboard they provide a nice set of guitar sounds to play with.
* GtrTeleLayered	106 multi-samples	An incredible Tele Thinline soundset. 3 Layers including a mute note on the lower velocities, a normal picked note on the middle velocities and an over picked note on the top velocities.
* GtrTeleChords	27 multi-samples	Open strummed major chords with one octave mapped to chunk style short chords, one octave mapped with the downstrokes and the last octave mapped with upstrokes. You can also program your own chords using the notes sets.

MT guitars - synth

CSGuitar	9 multi-samples	A nice plucked string chorus synth type guitar sound. These guitar synth sets are great on their own or layered with some of the other guitars for those "new world guitar" sounds.
MTDistSynGtr	9 multi-samples	A distorted and dirty style guitar synth soundset.
MTPluck01	11 multi-samples	Another nice clean plucked guitar type sound. Great on its own or for layering.

Creating your own soundsets

If you want to create your own soundsets for ManyGuitar (or ManyStation), you can. A (free) sample mapper is available from Manytone – you can download the sample mapper using the download link that you were sent when you were sent your download link for ManyGuitar.

ManyThanks

ManyThanks... Greg Schlaepfer

For his incredible work on the following Samplesets included in ManyGuitar:

- BassFingerFine
- BassFingerWarm
- GtrFunk
- GtrLeadGuitar1
- GtrLeadGuitar2

Also for his presets included with ManyGuitar, and his work on the new ManyTone Sample Mapper. Finally, a Big THANKS for the incredible Demo tracks.

ManyThanks... Berend (amoebe)

For the fantastic graphics on ManyGuitar and ManyMiniAmp.

ManyThanks... Simon Cann

For his continued effort to make the Manytone manuals, press releases, documents, photos and everything else involving “digital paper” the best they can be. Also, An extra big THANKS from Manytone is due, for all the website work Simon looked after for us. Thanks Simon!

ManyThanks... Luigi Felici (<http://nusofting.liqihsynth.com> and <http://dashsignature.com>) and Alan Diritto (<http://www.a0audio.com>) for the special attention to detail while coding ManyGuitar with us. “I had a tone in my head and you guys found it and built it in code ... Thanks!”

ManyThanks... Frank Genus (ToTc) (<http://www.totcproductions.com/>) for his Presets included with ManyGuitar and the late night email laughs ;-)

ManyThanks... Tim Conrardy (AlgoMusic: <http://www.algomusic.nl> and Tims Atari MIDI World: <http://tamw.atari-users.net>) for his Presets included with ManyGuitar.

ManyThanks... Stephan Müsch (rsmus7) for his Presets included with ManyGuitar.

ManyThanks... Ben at www.kvraudio.com for all he has done for the VSTi community and for hosting the Manytone Forum on the KvR site.

ManyThanks...

All of the beta testers and other people who have contributed something to this project. I know who you are and I appreciate all you have done.

ManyThanks...

My wife Karen for once again putting up with the huge Development time i put into ManyGuitar.

Also my 2 dogs and 2 cats, Bailey, Valentine, Scooter, and Quincy, for putting up with being Locked out of the Studio ;-) And for the Entertainment, and the Smiles they always bring to my face.

Disclaimer

This software is provided as is. Manytone and Dash Signature do not warrant in any way that the functions contained in the software will meet your requirements, or that the operation of the software will be uninterrupted or error-free, or that defects in the software will be corrected.

It is illegal to make copies and/or spread/publish the full version of the program its parts in any form without the written permission of Manytone. The registered user is not allowed to lend ManyGuitar to other persons, and he/she is also responsible for keeping ManyGuitar out of reach of unregistered users.

While efforts are made to ensure that the software and its documentation are free from defect, under no circumstances and under no legal theory, tort, contract, or otherwise, shall Manytone or Dash Signature, or their distributors or dealers be liable to you or any other person for any indirect, special, incidental, or consequential damages of any character including, without limitation, damages for loss of profit or goodwill, work stoppage, computer failure or malfunction, damage to hearing, damage of speakers and headphones or any and all other health and commercial damages or losses occasioned by the use of the software.

By using the software you accept all above.

Manytone/DASH Signature

© 2005 Manytone/DASH Signature